

商用高德对接说明书

序号	版本	更改内容	修订者	更改日期
1	1.0	初版下发	技术服务	20260616
2				
3				

免责声明

武汉微谷德技术有限公司提供的所有服务内容（包括程序、文档、测试结果、方案、支持等）仅供客户参考，旨在协助客户加速产品研发。本公司不对其完整性、可靠性等作任何保证。客户可自行选择使用或修改，因使用本文档内容所导致的任何特别、偶然或间接损失，本公司不承担责任。本规格书如有不影响产品性能及状态的更改，恕不另行通知。

目录

目录

一、 适用范围	3
二、 使用说明	3
1、 注册登录运营商账户	3
2、 接入高德及添加站点	3
(1) 平台操作路径	3
(2) 品牌名称及充电桩名称	3
(4) 高德经纬度	4
(5) 组织机构代码	4
(6) 地区及详细地址	4
(7) 其他信息	4
(8) 站点照片	4
(9) 收费信息	5
(10) 选填信息	5
(11) 绑定设备	5
(12) 进入审核	5
(13) 站点信息修改	5

一、适用范围

仅支持汽车充电桩（包含直流和交流以及三方对接设备），微谷德SAAS平台支持免费对接高德地图 不收取订单抽成。

二、使用说明

1、注册登录运营商账户

微信搜索公众号/服务号：微谷德。或扫描以下二维码进入微谷德SAAS平台。初次使用请使用手机号注册，如已有账号请直接登录商用后台操作，登录后点击右上角“体验新版”。



2、接入高德及添加站点

(1) 平台操作路径

点击右下角“我的”，点击页面中“高德接入” 点击页面中“添加站点”，填写站点信息，带红色*号为必填信息

(2) 品牌名称及充电桩名称

例：微谷德；充电桩名称：例：测试站

注意：

品牌名：以站点为单位，每个站点的品牌名可以不一致，品牌名需要给场站实际运营商的真实品牌名，品牌名尽量不要超过 5 个字，提供质检表时需确认好品牌名；

充电站名称：尽量以场站所在地标的主体命名，字数不能过长，最好不超过 10 个字，站名里不要写省市区，站名不要带有充电站避免重复。



(4) 高德经纬度

点击自动获取，进入地图后点击屏幕中间左侧蓝色小三角，然后点击我的位置，点击确定。坐标随即自动填入，无需再次手动填写。

(5) 组织机构代码

填写（这里填自己的品牌的组织机构代码）查询方式百度搜索 企查查 -> 输入框输入贵公司名称 -> 点击工商信息

(6) 地区及详细地址

先选择地区，如地区选项中无地址信息，请联系客服处理；详细地址无需填写省市区，具体位置描述需详细，场站在地上或地下停车场的话，位置需在描述中体现。

(7) 其他信息

服务电话、站点类型、站点状态、车位数量、建设场所、营业时间根据实际情况如实填写即可。

(8) 站点照片

每个站都要提供照片，照片越多越好，至少三张不同角度；需是场站实地照片，照片目的是方便我们在坐标周围寻找充电桩，照片中尽量包含更多要素以便在实际中去参照，不可对着桩拍；如果是地下站，需提供地下停车场入口处照片。

(9) 收费信息

根据实际情况如实填写即可。此为非必填信息，可根据设备实际情况填写。

(10) 选填信息

此为非必填信息，可根据设备实际情况填写。

(11) 绑定设备

站点添加完成后需在站点内添加设备，点击管理设备，添加设备，勾选已绑定的设备（未绑定设备需绑定），如包含直流设备，点击下方“是否包含直流设备”点击“是”，可填写参数。添加完成后也可点击管理设备，修改直流和交流设备参数。

(12) 进入审核

以上信息填写完毕，点击屏幕右下角确定即可，站点信息会进入后台审核阶段，审核约1-2个工作日，审核通过即完成高德对接，可进入高德APP搜索。

(13) 站点信息修改

后续修改站点信息可点击修改，1-2个工作日审核通过后更新。

The screenshots illustrate the app's workflow for station management:

- Screenshot 1 (Station Add/Edit):** Shows a form for adding or editing a station. Fields include brand name (谷德云), station name (测试), service phone (12345678970), business hours (00:00-24:00), station status (添加设备), and address (湖北省武汉市洪山区123). A red box highlights the '添加设备' (Add Equipment) button.
- Screenshot 2 (Equipment List):** Shows a list of equipment for a station. The list is currently empty, with a message '暂无数据' (No data). A red arrow points to the '添加设备' (Add Equipment) button at the bottom.
- Screenshot 3 (Equipment Selection):** Shows a list of equipment with checkboxes for selection. The list includes:
 - GD1B20588: 汽车交流充电桩 (Vehicle AC charging pile), status: 未绑定 (Not bound).
 - GD1B20685: 汽车交流充电桩 (Vehicle AC charging pile), status: 未绑定 (Not bound).
 - GD1B370577: 汽车交流充电桩 (Vehicle AC charging pile), status: 未绑定 (Not bound).
 - GD1B379851: 两轮智能充电桩 (Two-wheel smart charging pile), status: 未绑定 (Not bound).
 - GD1B389589: 两轮智能充电桩 (Two-wheel smart charging pile), status: 未绑定 (Not bound).
 A red box highlights the '是否包含直流设备' (Whether it includes DC equipment) section, which is currently set to '否' (No).
- Screenshot 4 (Parameter Modification):** Shows a '修改参数' (Modify Parameters) dialog box for a selected equipment. The parameters are:
 - 额定功率 (Rated Power): 9 KW
 - 额定电流 (Rated Current): 30 A
 - 最小电压 (Minimum Voltage): 90 V
 - 最大电压 (Maximum Voltage): 275 V
 A red arrow points to the '确定' (Confirm) button.